Howtoselectrightmodelofemulator

1. Modelofemulator:

With1.44MBcapacitydiskand34pinfloppydriverinterface

SFR1M44-FU

SFR1M44-FU-DL

SFR1M44-FUM-DL

SFR1M44-FEL-DL

SFR1M44-LUN

SFR1M44-U100K

SFR1M44-TU100K

With 720 KB capacity disk and 34 pinflo ppydriver interface:

SFRM72-FU

SFRM72-FU-EG

SFRM72-FU-DL

SFRM72-TU100K

With 26pinflatcablefloppydriverinterface

SFR1M44-DU26

SFRM72-DU26

SFR1M44-TU26

Modelformachinesepecified:

SFR1M44-SUE= Chineseembroiderymachinewithdahaomainboard,rec ognize DSTDSB formatonly

SFR1M44-JUK=JUKI210D sewingmachine

SHIMASFR1M2 -FU=SHIMASEIKISES flatknittingmachine

SFRM72-TU100UNI=MULLER1/2 labelweavingmachinewith UNIformat

SFR1M44-U100K-R=ROLANDG800E96 musickeyboard

2. Whatistheinterfaceo ffloppydriver:

IDC34pin+4Ppowerplug

IDC26 pin without additional power

FPC26flatcabel 1.0M Mpindistanceusemdoel SFR***-**26

FPC26 flatcabel 1.25MMpindistance

IDC34pinwithouradditionalpower

3. Whatisthecapacityofdisk

1.44MB1.2M B or 7 20Kbusedmodel SFR1M44-*** SFR1M2 -*** or SFRM72 -***

4. IstheformatofdiskFAT :

Openfloppy disk on computer, to confirm if the format of disk is FAT.

If not FAT, need to use WINHEX to try to read the image of floppy disk, if the disk image read successfull, and the contract of the contract

 $SFR ***-**-DL can be used \quad , or no model can be used.$

5. Modelusedinbulk:

Forembroiderymachine:

TAJIMAHAPPY with 1.44MB capacitydiskand 34pinfloppydriverinterfaceuse SFR1M44 -FU

TAJIMAHAPPYBARUDAN with720KBcapacitydiskand34pinfloppydriverinterfaceuse SFRM72-FU

BARUDANBENSwith720KBcapacitydiskand26pinflatcablefloppydriverinterfaceuse SFRM72-DU26

TAJIMA TMEG with 720KB capacity disk and 34pin floppy driver interface use SFRM72 -FU-EG(same

functionwithSFRM72 -FU,butbuilt -inmemorynotw ork whennousbstickplugedonemulator

Chineseembroiderymachinewithdahaomainboard SWF use SFR1M44-SUE

Flatknittingmachine:

STOLL with 1.44MB capacity disk and 34pin floppy driver interface use SFR1M44-LUN SFR1M44-FUM-DLSFR1M44 -U100K

SHIMA SEIKI SES series with 1.2MB capacity disk and 34pin floppy driver interface use SHIMA SFR1M2-FU

SHIMASEIKISES serieswith 1.44 MBcapaci tydiskand 34 pinfloppydriver interfaceuse SFR 1 M44-LUN

Labelweavingmachine:

MULLER3 STAUBLI -JC5 BONAS with 1.44MB capacity disk and 34pin floppy driver interface use SFR1M44-LUNSFR1M44 -U100K

STAUBLI-JC4 with1.44MBcapacitydiskand34pinfloppydriv erinterfaceuse SFR1M44-U100K MULLER1/2 with UNIformatuse SFRM72-TU100UNI

Musicinstrument:

YAMAHA KORG with 1.44MB capacity disk and 34pin floppy driver interface use SFR1M44-FUM-DL SFR1M44-U100K

ROLAND G800 E96 with 1.44MB capacity disk and 34pin flop py driver interface use SFR1M44-FU-DL SFR1M44-U100K-R

YAMAHA EL900 900M 900B 500 700 01C 01M with 1.44MB capacity disk and 34pin floppy driver interfaceuse SFR1M44-FEL-DL

Sewingmachine:

JUKI210D with1.44MBcapacitydiskand34pinfloppydriverinterfac euse SFR1M44-JUK

CNC:

MITSUBISHI200HA with720KBcapacitydiskand34pinfloppydriverinterfaceuse SFRM72-FU MITSUBISHIFA with1.44MBcapacitydiskand34pinfloppydriverinterfaceuse SFR1M44-LUN